

Manual

Note:

Support Digital Signal T2 S2

You can download the firmware from here:

<http://myosuploads3.banggood.com/products/20181221/20181221022350DANGKOURR52C04A.rar>

Description:

Model: RR52C.04A

Support TV Signal: DVB-C/T/T2/S2/ATV

Support Language: English, Chinese, French, Espanol, Deutsch, Nederlands, Portugues, German, Thai, Vietnam, Arabe.

Audio output power: 2x8W

Consumption: operating mode -> = 6W, simple - <0.3W

Video input: TV: DVB-T / T2 / S2, DVB-C, ANALOG TV (ATV), HDMI, VGA, AV IN

Input Interface: PC / HDMI / TV / USB multimedia playing

Voltage: DC 12V 4A

Screen interface: LVDS Single 6 / 8 , Double 6 / 8

Screen voltage: 3.3V / 5V / 12V

Resolution: Support high screen 1920 * 1080, 15-42 inch LVDS screen

Additional inputs outputs: audio mini jack 3.5mm USB

5 Built-in OSD Games, USB slot can be used for updating software and playing multi-media, such as Movie, MP3 and JPEG.text.

How to know if your panel suitable for this board?

Step 1: Find your LCD model's resolution (you can check the resolution from this link: <http://www.panelook.com/index.php>)

Step 2: Find and write in the corresponding firmware.

Step of USB upgrade:

1. Put the firmware of "RR52C.bin" in formatted USB flash disk ,then insert the USB disk and the 7KEY-Button to the board
2. After turn on the power, the light of the 7key button will be Red and flashing, after about 1 minute, the light stop flashing and be blue, it means upgrade has finished.(Note that write programs do not power outages, crashing won't be able to use)


How to into Factory setting?

Press "INPUT" button then press "1 1 4 7"


You can play game via this controller board, 5 built-in simple games: BOXMAN, HITRAT, TETRIS, GOBANG, SUDOKU.

Just have fun with this board, you will like it.

Press "INPUT" Choose "Game"



OSD GAME




BOXMAN




HITRAT



TETRIS



GOBANG



SUDOKU




Product Photos

LCD/LED Controller Board 5 built-in Games



5 OSD Games
DVB-S2/T2/T/C
DTV/ATV
HDMI/VGA IN
Dual USB IN
USB Play

Interface List




1. Main Power
2. INVERTER
3. DC 12V
4. VGA IN
5. HDMI IN
6. AV IN
7. Dual USB
8. PC AUDIO
9. Earphone

10. Tuner
11. S-Tuner
12. IR&KEY
13. LVDS
14. Speaker



Panel input Voltage: Factory default to 5V
Pls jump cap to the correct place for your panel.








Tuner

S-Tuner

Size











7 Key Button



Connection just for reference (For Panel no need inverter)



Below are the test Photos (take by us, Pls don't alter the pics)

Press Menu will see as below

1. Picture




2. Sound




3. Channel



4. Feature



5. Setup




PRESS "INPUT" will see as below



Then Choose "Media" into USB2.0, you can play photo/music/movie/text



1. PHOTO



You can also set boot logo

2. MUSIC



3. MOVIE




Notice:


High compression ratio files like MKV AVI may appear the situation like no sound or no display

you can transform them to RMVB/MP4 or other low compression ratio files.


4. e-book




Press "INPUT 1147" into "FACTORY SETTING"



If the lcd panel display is bad, you can adjust the LVDS parameter.



You can set the OSD language



You can also capture LOGO or Mirror display.